Hitachi StarBoard WT-1 graphics tablet

Bringing Wi-Fi control to your lessons or presentations

Easy to install and use, the new StarBoard WT-1 graphics tablet enables you to control your Hitachi interactive whiteboard from anywhere in the room.





The StarBoard WT-1 is a lightweight graphics tablet that enables you to control your lesson or lecture from anywhere in the room. Featuring Wi-Fi technology, the new WT-1 is quick and easy to install and simple to operate.

The WT-1 features 16 function buttons and a cordless pen to ensure easy control of your Hitachi interactive whiteboard. The device can be passed around the classroom for group members to contribute to lessons, training sessions or meetings without leaving their seat!



StarBoard WT-1 at a glance:

Key features

- 8" x 6" aspect ratio selectable writing area
- 16 function buttons
- Cordless pen
- Rolling area for volume control
- Page up and page down
- LCD display for status indication.
- Stand alone StarBoard software bundle an optional extra



recrimed specifications	
Wireless Tablet Hardware S	Specification
Solution:	Wireless 2.4G RF
Dimensions:	278mm(L) x 265mm(W) x 23mm(H)
Active area:	8" x 6"
Resolution:	2000 lpi
Report rate:	120 rps
Pen pressure:	1024 levels
Macro key:	16 (top of active area)
Hot key:	Page up / page down
Volume control method:	Circle Antenna
LCD type:	TN LCD
LCD size:	40.9 x 17.7mm
LCD Icon content:	Battery status – 4 levels & charged RF connected status; Pen detection status; Pen writing status Power on status Device connected number Volume control status (+ & -)
Feature:	Multiple pairing (1-50 or more)
Battery type:	US-W Li-ion rechargeable battery
Battery capacity:	700mA
Battery using time:	min. 16 hrs continuing mode
Battery life:	2 years
Power source:	USB charged / USB plus adaptor charged
Pen require:	T3A-020
Power button:	Electrical power button
Power consumption:	max. 50mA (operation mode)
Maximum writing height:	5mm
Maximum reading height:	10mm
Pen	
Pen tip:	Mouse left button, with pressure information
Lower barrel button:	Default as mouse right button (programmable)

Pen	
Pen tip:	Mouse left button, with pressure information
Lower barrel button:	Default as mouse right button (programmable)
Upper barrel button	Barrel 2 (programmable)
Tip travel:	2mm max.
Tip switch ON load:	Less than 38g
Battery:	AAA ×1

Please read safety instructions before using this product.

Further information:



Hitachi Australia Pty Ltd Level 3, 82 Waterloo Road North Ryde NSW 2113 Tel: +61 2 9888 4100 1800 HITACHI (Australia only) Fax: +61 2 9888 4188 Email: dps@hitachi.com.au

www.hitachi.com.au

